

USER MANUAL



MINI CAMERA

Please read this user manual carefully and thoroughly before any attempt to operate this product and retain it for your future reference.

FEATUERS:

- *Innovative Back-Splint design
- *360 degrees rotated Clip
- *HD 1920*1080P @30FPS
- *4 pcs Leds ,support night vision
- *Battery standby time is about 6 hours
- *Built-in 16/32gb memory card (optional)
- *Built-in 800mah battery , 4 hours working

DETAILED IMAGES:



Note: This item is without waterproof.

OPEARTIONS:

Note: Please charge about 3.5 hours before using .

The default state of this product is circularly covering the recorded video, when the capacity of the memory card is less than 400MB , the system will automatically cover the previous video ,and the file can't be recovered .Use this function with caution

1. CHAGRING:

The Mini Camera has an internal battery .The battery can be charged as following:

Please use the original USB cable , plug the type-c connector into the camera and the normal USB plug in your computer ,power bank ,or use an external 5V 1A Charger. Charging time is about 3.5 hours.

Note:Red led lights is on while charging , once full charged , red led turns off.If red led light blinks 10 times and the camera shuts down,it means the battery is low .

2. POWERING THE CAMERA ON/OFF:

Long press the power button for 3 seconds to turn on the camera. The blue led will light up .

Long press on/off button for 3 seconds to turn off the camera. The blue led will blink 9 times.

Note: The battery standby time is about 6 hours while the camera is on .

3. VIDEO RECORDING:

(1) Long press the power button for 3 seconds to turn on the camera. The blue led will light up . Press the on/off button to start recording . The blue led will flash 4 times before recording. During the recording led light is off . Press on/off button again to stop recording . The blue led returns to blue (standby state).

(2) Press on/off button again to start another recording .

Note: For long time recording , the video

streaming is divided into files each 5 minutes.

4. NIGHT VISION ON/OFF:

To activate night vision mode, make sure that the camera is on. Quickly twice press the on/off button, then the blue led will flash one time and the night vision IR Led is on. Quickly twice press the on/off button to turn off night vision. then the red led light will flash one time and night vision is off.

5. RESETTING THE CAMERA:

When the camera works abnormally, you can try to reset it.

To reset, insert pin to the reset hole,press one time, the led light will turn off and reset is done.

Restart the camera , it may be work normally .

Note:Please do not insert the pin to the other hole.

6. VIDEO REPLAY

Long press power button for 3 seconds to turn on the camera ,and blue led will light up . Connect camera to computer or laptop with the usb cable. Plug type-c connector into the camera and the normal USB plug into the

computer or laptop. A new removable disk will appear on the computer screen. Open the removable disk to view the videos .

7. TIME STAMP:

Long press power button for 3 seconds to turn on the camera. The blue led will light up . Connect the camera to the computer via USB cable. The camera will create a “txt” file (userconfig) in the removable disk . Open the text “userconfig” file to revise the display time / date on your video .

The format is :

2018-10-12-01:15:59=Y

Year-Month-Day-Hour:Minute:Second=Y

2018-10-12-01:15:59=N

Year-Month-Day-Hour:Minute:Second=N

Note: Y for display , N for no display .

After setting is done, turn on the camera . The blue led light will flash while the time-stamp is upgrading . Once upgrading is complete , the blue led light is turned off and the camera is turned off .

8. RELEVANT PARAMETERS:

Items	Relevant Parameters
Video Resolution	1920*1080P
Video Format	AVI
Video Coding	M-JPEG
Video Frames	30fps
Storage	Built-in Memory Card
Type of Interface	Type-C
Battery Capacity	Built-in 800mah
Standby Time	About 6 hours
Working Duration	About 4 hours
Charging Voltage	DC = 5V